

PITFALL II

OPCION DE JUGADORES POR MONEDA

DIP SWITCH A


	1	2	3	4	5	6	7	8
1 MONEDA 1 CREDITO	OFF	OFF	OFF	OFF	OFF	OFF	OFF	OFF
1 MONEDA 2 CREDITOS	ON	OFF	OFF	OFF	ON	OFF	OFF	OFF
1 MONEDA 3 CREDITOS	OFF	ON	OFF	OFF	OFF	ON	OFF	OFF
1 MONEDA 4 CREDITOS	ON	ON	OFF	OFF	ON	ON	OFF	OFF
1 MONEDA 5 CREDITOS	OFF	OFF	ON	OFF	OFF	OFF	ON	OFF
1 MONEDA 6 CREDITOS	ON	OFF	ON	OFF	ON	OFF	ON	OFF
2 MONEDAS 1 CREDITO	OFF	ON	ON	OFF	OFF	ON	ON	OFF
3 MONEDAS 1 CREDITO	ON	ON	ON	OFF	ON	ON	ON	OFF
4 MONEDAS 1 CREDITO	OFF	OFF	OFF	ON	OFF	OFF	OFF	ON
2 MONEDAS 3 CREDITOS	ON	OFF	OFF	ON	ON	OFF	OFF	ON
2 MONEDAS 1 CREDITO								
4 MONEDAS 2 CREDITOS	OFF	ON	OFF	ON	OFF	ON	OFF	ON
5 MONEDAS 3 CREDITOS								
6 MONEDAS 4 CREDITOS								
1 MONEDAS 1 CREDITO								
2 MONEDAS 2 CREDITOS								
3 MONEDAS 3 CREDITOS	OFF	OFF	ON	ON	OFF	OFF	ON	ON
4 MONEDAS 4 CREDITOS								
5 MONEDAS 6 CREDITOS								
1 MONEDA 1 CREDITO								
2 MONEDAS 2 CREDITOS	ON	OFF	ON	ON	ON	OFF	ON	ON
3 MONEDAS 3 CREDITOS								
4 MONEDAS 5 CREDITOS								
1 MONEDA 1 CREDITO	OFF	ON	ON	ON	OFF	ON	ON	ON
2 MONEDAS 3 CREDITOS								
1 MONEDA 1 CREDITO	ON	ON	ON	ON	ON	ON	ON	ON
2 MONEDAS 1 CREDITO	ON	ON	OFF	ON	ON	ON	OFF	ON
4 MONEDAS 2 CREDITOS								

DIP SWITCH B

[illegible]

MASA
 AZUL
 ROJO
 ALTAVOZ
 PULSADOR DE SERVICIO
 PULSADOR DE TEST
 MONEDERO 2
 MONEDERO 1
 1 J. IZQUIERDA
 1 J. DERECHA
 1 J. ARRIBA
 1 J. ABAJO
 NO CONECTAR
 1 J. SALTO
 NO CONECTAR
 NO CONECTAR
 + 12 V.
 CONTADOR MONEDA 1
 + 5 V.
 + 5 V.
 MASA
 MASA

CARA COMPON.




CARA SOLDADURA

MASA
 SINCRONISMO
 VERDE
 ALTAVOZ
 NO CONECTAR
 NO CONECTAR
 2 J. INICIO
 1 J. INICIO
 2 J. IZQUIERDA
 2 J. DERECHA
 2 J. ARRIBA
 2 J. ABAJO
 NO CONECTAR
 2 J. SALTO
 NO CONECTAR
 NO CONECTAR
 NO CONECTAR
 CONTADOR MONEDA 2
 + 5 V.
 + 5 V.
 MASA
 MASA


DIP SW A

DIP SW B



PLACA CIRCUITO IMPR.
No. 171-5054-02

DIREC. DE LA PALANCA DE CONTROL



SALTOS

TENSIONES & CORRIENTES

VOLTAJE	INTENSIDAD
DC 5 V.	4, 1 A
DC 12 V.	0, 25 A