



- CONTADOR-A
- CONTADOR-B
- + 5 Vcc
- SALIDA A
- SALIDA B
- ENTRADA MONEDERO B
- ENTRADA MONEDERO A
- GND

SW-1

3	2	1	MONEDAS-A
ON	ON	ON	1
ON	ON	OFF	2
ON	OFF	ON	3
ON	OFF	OFF	4
OFF	ON	ON	5
OFF	ON	OFF	6
OFF	OFF	ON	7
OFF	OFF	OFF	8

SW-1

6	5	4	CREDITOS-A
ON	ON	ON	1
ON	ON	OFF	2
ON	OFF	ON	3
ON	OFF	OFF	4
OFF	ON	ON	5
OFF	ON	OFF	6
OFF	OFF	ON	7
OFF	OFF	OFF	8

SW-1

7	
ON	2 ENTRADAS 2 SALIDAS
OFF	2 ENTRADA 1 SALIDA-A

SW-2

3	2	1	MONEDAS-B
ON	ON	ON	1
ON	ON	OFF	2
ON	OFF	ON	3
ON	OFF	OFF	4
OFF	ON	ON	5
OFF	ON	OFF	6
OFF	OFF	ON	7
OFF	OFF	OFF	8

SW-2

6	5	4	CREDITOS-B
ON	ON	ON	1
ON	ON	OFF	2
ON	OFF	ON	3
ON	OFF	OFF	4
OFF	ON	ON	5
OFF	ON	OFF	6
OFF	OFF	ON	7
OFF	OFF	OFF	8

SW-2

8	7	DURACION PULSO
ON	ON	CORTO
ON	OFF	LARGO

SE PUEDE HACER CUALQUIER TIPO DE COMBINACION ENTRE MONEDAS Y CREDITOS, DE LOS DOS MONEDEROS INDISTINTAMENTE.